





- 0.4% Initial Voltage Tolerance
- 0.2- $\Omega$  Typical Output Impedance
- Fast Turnon . . . 500 ns
- Sink Current Capability . . . 1 mA to 100 mA
- Low Reference Current (REF)
- Adjustable Output Voltage . . .  $V_{I(REF)}$  to 36 V




NC – No internal connection  
ANODE terminals are connected internally.



NC – No internal connection



The ANODE terminal is in electrical contact with the mounting base.



## description/ordering information

The TL1431 is a precision programmable reference with specified thermal stability over automotive, commercial, and military temperature ranges. The output voltage can be set to any value between  $V_{I(REF)}$  (approximately 2.5 V) and 36 V with two external resistors (see Figure 16). This device has a typical output impedance of 0.2  $\Omega$ . Active output circuitry provides a very sharp turnon characteristic, making the device an excellent replacement for Zener diodes and other types of references in applications such as onboard regulation, adjustable power supplies, and switching power supplies.

The TL1431C is characterized for operation over the commercial temperature range of 0°C to 70°C. The TL1431Q is characterized for operation over the full automotive temperature range of -40°C to 125°C. The TL1431M is characterized for operation over the full military temperature range of -55°C to 125°C.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

**TEXAS  
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 2004, Texas Instruments Incorporated  
On products compliant to MIL-PRF-38535, all parameters are tested unless otherwise noted. On all other products, production processing does not necessarily include testing of all parameters.

TL1431  
PRECISION PROGRAMMABLE REFERENCE

SLVS062J – DECEMBER 1991 – REVISED FEBRUARY 2004


description/ordering information (continued)

ORDERING INFORMATION


TA	PACKAGE†		ORDERABLE PART NUMBER	TOP-SIDE MARKING
0°C to 70°C	POWER-FLEX (KTP)	Reel of 3000	TL1431CKTPR	TL1431C
	SOIC (D)	Tube of 75	TL1431CD	1431C
		Reel of 2500	TL1431CDR	
	TO-226 / TO-92 (LP)	Bulk of 1000	TL1431CLP	TL1431C
		Reel of 2000	TL1431CLPR	
	TSSOP (PW)	Tube of 150	TL1431CPW	T1431
		Reel of 2000	TL1431CPWR	
-40°C to 125°C	SOIC (D)	Tube of 75	TL1431QD	TL1431QD
		Reel of 2500	TL1431QDR	
	TO-226 / TO-92 (LP)	Bulk of 1000	TL1431QLP	TL1431QLP
		Reel of 2000	TL1431QLPR	
	TSSOP (PW)	Tube of 150	TL1431QPW	T1431QPW
		Reel of 2000	TL1431QPWR	
-55°C to 125°C	CDIP (JG)	Tube of 50	TL1431MJG	TL1431MJG
	LCCC (FK)	Tube of 55	TL1431MFK	TL1431MFK

† Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at [www.ti.com/sc/package](http://www.ti.com/sc/package).


symbol



functional block diagram



### equivalent schematic†



† All component values are nominal.  
Pin numbers shown are for the D package.

### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Cathode voltage, $V_{KA}$ (see Note 1)	37 V
Continuous cathode current range, $I_{KA}$	–100 mA to 150 mA
Reference input current range, $I_{I(ref)}$	–50 $\mu$ A to 10 mA
Package thermal impedance, $\theta_{JA}$ (see Notes 2 and 3): D package	97°C/W
(see Notes 2 and 4): KTP package	28°C/W
(see Notes 2 and 3): LP package	140°C/W
(see Notes 2 and 3): PW package	149°C/W
Package thermal impedance, $\theta_{JC}$ (see Notes 5 and 6): FK package	5.61°C/W
JG package	14.5°C/W
Operating virtual junction temperature, $T_J$	150°C
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds	260°C
Storage temperature range, $T_{stg}$	–65°C to 150°C

‡ Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES:
1. All voltage values are with respect to ANODE, unless otherwise noted.
  2. Maximum power dissipation is a function of  $T_J(max)$ ,  $\theta_{JA}$ , and  $T_A$ . The maximum allowable power dissipation at any allowable ambient temperature is  $P_D = (T_J(max) - T_A)/\theta_{JA}$ . Operating at the absolute maximum  $T_J$  of 150°C can affect reliability.
  3. The package thermal impedance is calculated in accordance with JESD 51-7.
  4. The package thermal impedance is calculated in accordance with JESD 51-5.
  5. Maximum power dissipation is a function of  $T_J(max)$ ,  $\theta_{JC}$ , and  $T_C$ . The maximum allowable power dissipation at any allowable case temperature is  $P_D = (T_J(max) - T_C)/\theta_{JC}$ . Operating at the absolute maximum  $T_J$  of 150°C can affect reliability.
  6. The package thermal impedance is calculated in accordance with MIL-STD-883.

# TL1431

## PRECISION PROGRAMMABLE REFERENCE

SLVS062J – DECEMBER 1991 – REVISED FEBRUARY 2004

### recommended operating conditions

			MIN	MAX	UNIT
V <sub>KA</sub>	Cathode voltage		V <sub>I(ref)</sub>	36	V
I <sub>KA</sub>	Cathode current		1	100	mA
T <sub>A</sub>	Operating free-air temperature	TL1431C	0	70	°C
		TL1431Q	–40	125	
		TL1431M	–55	125	

### electrical characteristics at specified free-air temperature, I<sub>KA</sub> = 10 mA (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T <sub>A</sub> †	TEST CIRCUIT	TL1431C			UNIT
				MIN	TYP	MAX	
V <sub>I(ref)</sub>	Reference input voltage	25°C	Figure 1	2490	2500	2510	mV
		Full range		2480		2520	
V <sub>I(dev)</sub>	Deviation of reference input voltage over full temperature range‡	Full range	Figure 1		4	20	mV
$\frac{\Delta V_{I(ref)}}{\Delta V_{KA}}$	Ratio of change in reference input voltage to the change in cathode voltage	Full range	Figure 2		–1.1	–2	mV/V
I <sub>I(ref)</sub>	Reference input current	25°C	Figure 2		1.5	2.5	µA
		Full range				3	
I <sub>I(dev)</sub>	Deviation of reference input current over full temperature range‡	Full range	Figure 2		0.2	1.2	µA
I <sub>min</sub>	Minimum cathode current for regulation	25°C	Figure 1		0.45	1	mA
I <sub>off</sub>	Off-state cathode current	25°C	Figure 3		0.18	0.5	µA
		Full range				2	
z <sub>KA</sub>	Output impedance§	25°C	Figure 1		0.2	0.4	Ω


† Full range is 0°C to 70°C for C-suffix devices.

‡ The deviation parameters V<sub>I(dev)</sub> and I<sub>I(dev)</sub> are defined as the differences between the maximum and minimum values obtained over the rated temperature range. The average full-range temperature coefficient of the reference input voltage  $\alpha_{V_{I(ref)}}$  is defined as:

$$\left| \alpha_{V_{I(ref)}} \right| \left( \frac{\text{ppm}}{^{\circ}\text{C}} \right) = \frac{\left( \frac{V_{I(dev)}}{V_{I(ref)} \text{ at } 25^{\circ}\text{C}} \right) \times 10^6}{\Delta T_A}$$

where:

$\Delta T_A$  is the rated operating temperature range of the device.



$\alpha_{V_{I(ref)}}$  is positive or negative, depending on whether minimum V<sub>I(ref)</sub> or maximum V<sub>I(ref)</sub>, respectively, occurs at the lower temperature.

§ The output impedance is defined as:  $|z_{KA}| = \frac{\Delta V_{KA}}{\Delta I_{KA}}$

When the device is operating with two external resistors (see Figure 2), the total dynamic impedance of the circuit is given by:  $|z'| = \frac{\Delta V}{\Delta I}$ ,

which is approximately equal to  $|z_{KA}| \left( 1 + \frac{R1}{R2} \right)$ .

**electrical characteristics at specified free-air temperature,  $I_{KA} = 10$  mA (unless otherwise noted)**

PARAMETER	TEST CONDITIONS	$T_A$ †	TEST CIRCUIT	TL1431Q			TL1431M			UNIT
				MIN	TYP	MAX	MIN	TYP	MAX	
$V_{I(ref)}$ Reference input voltage	$V_{KA} = V_{I(ref)}$	25°C	Figure 1	2490	2500	2510	2475	2500	2540	mV
		Full range		2470		2530	2460		2550	
$V_{I(dev)}$ Deviation of reference input voltage over full temperature range‡	$V_{KA} = V_{I(ref)}$	Full range	Figure 1		17	55		17	55*	mV
$\frac{\Delta V_{I(ref)}}{\Delta V_{KA}}$ Ratio of change in reference input voltage to the change in cathode voltage	$\Delta V_{KA} = 3$ V to 36 V	Full range	Figure 2		-1.1	-2		-1.1	-2	mV/V
$I_{I(ref)}$ Reference input current	$R1 = 10$ k $\Omega$ , $R2 = \infty$	25°C	Figure 2		1.5	2.5		1.5	2.5	$\mu$ A
		Full range				4			5	
$I_{I(dev)}$ Deviation of reference input current over full temperature range‡	$R1 = 10$ k $\Omega$ , $R2 = \infty$	Full range	Figure 2		0.5	2		0.5	3*	$\mu$ A
$I_{min}$ Minimum cathode current for regulation	$V_{KA} = V_{I(ref)}$	25°C	Figure 1		0.45	1		0.45	1	mA
$I_{off}$ Off-state cathode current	$V_{KA} = 36$ V, $V_{I(ref)} = 0$	25°C	Figure 3		0.18	0.5		0.18	0.5	$\mu$ A
		Full range				2			2	
$ z_{KA} $ Output impedance§	$V_{KA} = V_{I(ref)}$ , $f \leq 1$ kHz, $I_{KA} = 1$ mA to 100 mA	25°C	Figure 1		0.2	0.4		0.2	0.4	$\Omega$

\*On products compliant to MIL-PRF-38535, this parameter is not production tested.


† Full range is -40°C to 125°C for Q-suffix devices and -55°C to 125°C for M-suffix devices.

‡ The deviation parameters  $V_{I(dev)}$  and  $I_{I(dev)}$  are defined as the differences between the maximum and minimum values obtained over the rated temperature range. The average full-range temperature coefficient of the reference input voltage  $\alpha_{V_{I(ref)}}$  is defined as:

$$|\alpha_{V_{I(ref)}}| \left( \frac{\text{ppm}}{^{\circ}\text{C}} \right) = \frac{\left( \frac{V_{I(dev)}}{V_{I(ref)} \text{ at } 25^{\circ}\text{C}} \right) \times 10^6}{\Delta T_A}$$

where:

$\Delta T_A$  is the rated operating temperature range of the device.



$\alpha_{V_{I(ref)}}$  is positive or negative, depending on whether minimum  $V_{I(ref)}$  or maximum  $V_{I(ref)}$ , respectively, occurs at the lower temperature.

§ The output impedance is defined as:  $|z_{KA}| = \frac{\Delta V_{KA}}{\Delta I_{KA}}$

When the device is operating with two external resistors (see Figure 2), the total dynamic impedance of the circuit is given by:  $|z'| = \frac{\Delta V}{\Delta I}$ ,

which is approximately equal to  $|z_{KA}| \left( 1 + \frac{R1}{R2} \right)$ .

PARAMETER MEASUREMENT INFORMATION




Figure 1. Test Circuit for  $V_{(KA)} = V_{ref}$




Figure 2. Test Circuit for  $V_{(KA)} > V_{ref}$




Figure 3. Test Circuit for  $I_{off}$

TYPICAL CHARACTERISTICS

Table of Graphs

	FIGURE
Reference voltage vs Free-air temperature	4
Reference current vs Free-air temperature	5
Cathode current vs Cathode voltage	6, 7
Off-state cathode current vs Free-air temperature	8
Ratio of delta reference voltage to delta cathode voltage vs Free-air temperature	9
Equivalent input-noise voltage vs Frequency	10
Equivalent input-noise voltage over a 10-second period	11
Small-signal voltage amplification vs Frequency	12
Reference impedance vs Frequency	13
Pulse response	14
Stability boundary conditions	15

TYPICAL CHARACTERISTICS†




Figure 4




Figure 5




Figure 6




Figure 7

† Data at high and low temperatures are applicable only within the recommended operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS†




Figure 8




Figure 9






Figure 10

† Data at high and low temperatures are applicable only within the recommended operating free-air temperature ranges of the various devices.



## TYPICAL CHARACTERISTICS

### EQUIVALENT INPUT-NOISE VOLTAGE OVER A 10-SECOND PERIOD



TEST CIRCUIT FOR 0.1-Hz TO 10-Hz EQUIVALENT INPUT-NOISE VOLTAGE

Figure 11

TYPICAL CHARACTERISTICS





Figure 12






Figure 13



APPLICATION INFORMATION

Table of Application Circuits

APPLICATION	FIGURE
Shunt regulator	16
Single-supply comparator with temperature-compensated threshold	17
Precision high-current series regulator	18
Output control of a three-terminal fixed regulator	19
Higher-current shunt regulator	20
Crowbar	21
Precision 5-V, 1.5-A, 0.5% regulator	22
5-V precision regulator	23
PWM converter with 0.5% reference	24
Voltage monitor	25
Delay timer	26
Precision current limiter	27
Precision constant-current sink	28



NOTE A: R should provide cathode current  $\geq 1$  mA to the TL1431 at minimum  $V_{(BATT)}$ .

Figure 16. Shunt Regulator






Figure 17. Single-Supply Comparator With Temperature-Compensated Threshold

## APPLICATION INFORMATION




NOTE A: R should provide cathode current  $\geq 1$  mA to the TL1431 at minimum  $V(\text{BATT})$ .


**Figure 18. Precision High-Current Series Regulator**



**Figure 19. Output Control of a Three-Terminal Fixed Regulator**



**Figure 20. Higher-Current Shunt Regulator**



NOTE A: Refer to the stability boundary conditions in Figure 15 to determine allowable values for C.

**Figure 21. Crowbar**

# TL1431 PRECISION PROGRAMMABLE REFERENCE

SLVS062J – DECEMBER 1991 – REVISED FEBRUARY 2004

## APPLICATION INFORMATION





Figure 22. Precision 5-V, 1.5-A, 0.5% Regulator



NOTE A:  $R_b$  should provide cathode current  $\geq 1\text{ mA}$  to the TL1431.

Figure 23. 5-V Precision Regulator






Figure 24. PWM Converter With 0.5% Reference


## APPLICATION INFORMATION




**Figure 25. Voltage Monitor**



**Figure 26. Delay Timer**



**Figure 27. Precision Current Limiter**



**Figure 28. Precision Constant-Current Sink**

## JG (R-GDIP-T8)

## CERAMIC DUAL-IN-LINE



- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - C. This package can be hermetically sealed with a ceramic lid using glass frit.
  - D. Index point is provided on cap for terminal identification.
  - E. Falls within MIL STD 1835 GDIP1-T8



FK (S-CQCC-N\*\*)

LEADLESS CERAMIC CHIP CARRIER


28 TERMINAL SHOWN



- NOTES:
- All linear dimensions are in inches (millimeters).
  - This drawing is subject to change without notice.
  - This package can be hermetically sealed with a metal lid.
  - The terminals are gold plated.
  - Falls within JEDEC MS-004


## KTP (R-PSFM-G2)

## PowerFLEX™ PLASTIC FLANGE-MOUNT PACKAGE



- NOTES:
- All linear dimensions are in inches (millimeters).
  - This drawing is subject to change without notice.
  - The center lead is in electrical contact with the thermal tab.
  - Dimensions do not include mold protrusions, not to exceed 0.006 (0,15).
  - Falls within JEDEC TO-252 variation AC.


PowerFLEX is a trademark of Texas Instruments.

**D (R-PDSO-G\*\*)****PLASTIC SMALL-OUTLINE PACKAGE****8 PINS SHOWN**

- NOTES: A. All linear dimensions are in inches (millimeters).  
 B. This drawing is subject to change without notice.  
 C. Body dimensions do not include mold flash or protrusion, not to exceed 0.006 (0,15).  
 D. Falls within JEDEC MS-012

## LP (O-PBCY-W3)

## PLASTIC CYLINDRICAL PACKAGE




- NOTES: A. All linear dimensions are in inches (millimeters).  
 B. This drawing is subject to change without notice.  
 C. Lead dimensions are not controlled within this area  
 D. Falls within JEDEC TO -226 Variation AA (TO-226 replaces TO-92)  
 E. Shipping Method:  
     Straight lead option available in bulk pack only.  
     Formed lead option available in tape & reel or ammo pack.

# MECHANICAL DATA

MSOT002A – OCTOBER 1994 – REVISED NOVEMBER 2001

LP (O-PBCY-W3)

PLASTIC CYLINDRICAL PACKAGE



- NOTES: A. All linear dimensions are in inches (millimeters).  
B. This drawing is subject to change without notice.  
C. Tape and Reel information for the Format Lead Option package.

## PW (R-PDSO-G\*\*)

## PLASTIC SMALL-OUTLINE PACKAGE

14 PINS SHOWN



- NOTES:
- All linear dimensions are in millimeters.
  - This drawing is subject to change without notice.
  - Body dimensions do not include mold flash or protrusion not to exceed 0,15.
  - Falls within JEDEC MO-153

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

<b>Products</b>		<b>Applications</b>	
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>	Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>	Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>	Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>	Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>	Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>	Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>	Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
		Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
		Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
		Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments  
Post Office Box 655303 Dallas, Texas 75265

Copyright © 2004, Texas Instruments Incorporated